

SECTION 16050 - BASIC ELECTRICAL REQUIREMENTS

PART 1 - GENERAL

1.01 SUMMARY

- A. Section Includes: General administrative, procedural requirements, and installation methods for electrical installations specified in Division 16.
- B. The Drawings are schematic and are not intended to show every detail of construction.
 - 1. In general, conduits/raceways, transitions and offsets shown on Drawings indicate approximate locations in plan and elevation where the systems are intended to be run.
 - 2. CONTRACTOR shall fully coordinate electrical Work with other trades to avoid interferences.
 - 3. In the event of interferences, CONTRACTOR shall request clarification from ENGINEER in writing.
- B. Related Documents
 - 1. Drawings and general provisions of Contract, including General and Supplementary Conditions and Division 1 Sections, apply to Work of this Section.
 - 2. See attached for templates and examples of other required submittals.

1.02 SUBMITTALS

- A. Shop Drawings: Submit in accordance with requirements of Section 01300, Shop Drawings covering the items included under this Section of Work. Shop Drawing submittals shall include:
 - 1. Submit product data covering the items included under this Section of Work.
- B. Conforming to Construction Drawings: Submit a complete set of Drawings showing the locations of the piping, ductwork, etc., as actually installed. Such Drawings shall be submitted to ENGINEER. Provide three (3) hard copy sets, and three (3) PDF sets on individual jump drives.
- C. Operation and Maintenance Manuals: Submit in accordance with requirements of Section 01782, operation and maintenance manuals for items included under this Section. Include following information for equipment items:
 - 1. Description of function, normal operating characteristics and limitations, performance curves, engineering data and tests, and complete nomenclature and commercial numbers of replacement parts.
 - 2. Manufacturer's printed operating procedures to include start-up, break-in, and routine and normal operating instructions; regulation, control, stopping, shutdown, and emergency instructions; and summer and winter operating instructions.
 - 3. Maintenance procedures for routine preventative maintenance and troubleshooting; disassembly, repair, and reassembly; aligning and adjusting instructions.
 - 4. Servicing instructions and lubrication charts and schedules.

1.03 RECORD DOCUMENTS

- A. Prepare Record Documents in accordance with requirements in Section 01700. In addition, CONTRACTOR shall submit, prior to final payment, Drawings conforming to construction records of systems it has installed. Vendor drawings shall be sized as manufacturers' standard.

- B. Provide typewritten data sheets on motor control circuits with following information on each branch feeder: Load name, horsepower or KVA (transformer), fuse size, starter size, service factor of motor, motor nameplate currents, power factor correction capacitor size (if used), and thermal overload part number.

1.04 QUALITY ASSURANCE

- A. National Electrical Code:
 - 1. Comply with NFPA 70, National Electrical Code.
 - 2. Comply with NFPA 70E, Electrical Safety
 - 3. Comply with NFPA 820, Standard for Fire Protection in Wastewater Treatment and Collection Facilities
- B. UL Compliance and Labeling: Use products and components labeled by UL.

1.05 PERMITS, INSPECTIONS, AND LICENSES

- A. CONTRACTOR shall procure all necessary permits and licenses, observe and abide by all applicable laws, codes, regulations, ordinances, and rules of the State, territory, or political subdivision thereof, wherein Work is done, or any other duly constituted public authority, and further agrees to hold OWNER harmless from liability or penalty which might be imposed by reason of an asserted violation of such laws, codes, regulations, ordinances, or other rules.
 - 1. Upon completion of Work, CONTRACTOR shall secure certificates of inspection from the inspector having jurisdiction and shall submit 3 copies of the certificates to OWNER. CONTRACTOR shall pay the fees for the permits, inspections, licenses, and certifications when such fees are required.

1.06 DELIVERY, STORAGE, AND HANDLING

- A. Deliver products to Project properly identified with names, model numbers, types, grades, compliance labels, and other information needed for identification. Equipment shall be packaged to prevent damage during shipment, storage, and handling. Do not install damaged units; replace and remove damaged units from Site.

PART 2 - PRODUCTS

2.01 EQUIPMENT

- A. Provide the OWNER a Fluke 325 Clamp Meter, digital clamp-on ammeter.
- B. Provide the OWNER a Fluke 709H Calibrator for contracts that include field instrumentation.
- C. Provide manufacturer configuration and calibration software, and equipment required by the manufacturer for furnished instruments.

PART 3 - EXECUTION

3.01 GENERAL ELECTRICAL INSTALLATION

- A. Provide electrical materials and equipment enclosures appropriate for areas in which they are installed. Each area will be designated on Drawings with a type of construction such as NEMA 4, 4X, 7 or 9 if it is other than NEMA 12. An area designated by a name and elevation includes space bounded by floor, ceiling, and enclosing walls.
 - 1. Exception: Provide manufacturer's standard construction for indoor or outdoor application where equipment is not manufactured to NEMA specifications (e.g., switchgear, transformers, high voltage capacitors, bus duct, and light fixtures; materials and equipment used in finished areas such as offices, laboratories, etc.).
- B. Provide nonmetallic electrical materials and equipment enclosures in NEMA 4X areas; watertight NEMA 4 and equipment enclosures for outdoor applications and indoor applications below grade; explosion-proof NEC Class I, Division 1, Group D equipment for NEMA 7 areas; explosion-proof NEC Class II, Division 2, Group F equipment for NEMA 9 areas.
- C. Coordinate with power company high voltage and/or low voltage metering requirements. Furnish, install, and connect metering equipment not furnished, installed or connected by power company.
- D. Coordinate with telephone company the communication service requirements. Furnish, install, and connect cable and terminal equipment not furnished, installed, or connected by telephone company. Furnish and install a 4-foot by 8-foot by 3/4-inch plywood backboard painted white, raceway from backboard to property line, and cross-connect base and blocks which utilize punchdown wiring methodology.
- E. Provide chases, slots, and openings in other building components during progress of construction, to allow for electrical installations.
- F. Supporting devices and sleeves shall be set in poured-in-place concrete and other structural components as they are constructed.
- G. Where mounting heights are not detailed or dimensioned, install systems, materials, and equipment to provide maximum headroom possible. Locate light fixtures at approximately 8 feet above floor and where fixtures may be readily serviced.
- H. Coordinate connection of electrical systems with exterior underground and overhead utilities and services. Comply with requirements of governing regulations, franchised service companies, and controlling agencies. Provide required connection for each service.
- I. Per NEC 210.8.B Exception 3, do not provide GFI receptacles/circuits for sump pumps or heat tape.
- J. Install systems, materials, and equipment to conform with approved submittal data, including coordination Drawings, to greatest extent possible. Conform to arrangements indicated by Drawings recognizing that portions of Work are shown only in diagrammatic form. Where coordination requirements conflict with individual system requirements, refer conflict to ENGINEER.
- K. Install systems, materials, and equipment level and plumb, parallel and perpendicular to other building systems and components where installed exposed in finished spaces.
- L. As much as practical, connect equipment for ease of disconnecting with minimum of interference with other installations.

- M. Install access panel or doors where units are concealed behind finished surfaces. Access panels and doors are specified in Section 08310.
- N. Install systems, materials, and equipment giving right-of-way priority to systems required to be installed at a specified slope.

3.02 RACEWAY INSTALLATION

- A. Outdoors, use the following materials:
 - 1. Exposed Conduit: PVC externally coated rigid metal conduit and fittings or galvanized with prior OWNER approval.
 - 2. Underground Direct Buried Conduit:
 - a. PVC externally coated rigid metal conduit (Analog/VFD wiring).
 - b. PVC Schedule 80 (power/control wiring)
 - 3. Underground Concrete Encased Conduit: Fiberglass-reinforced conduit or rigid nonmetallic conduit if the conductors are used for power or 120 VAC; otherwise, use rigid metal conduit.
 - 4. Conduit Used to Connect to Vibrating Equipment including transformers and hydraulic, pneumatic or electric solenoid or motor-driven equipment: Liquidtight flexible non-metallic conduit.
 - a. Public accessible locations shall have liquidtight flexible metal conduit.
- B. Indoors, use the following wiring materials:
 - 1. Connection to Vibrating Equipment, including transformers and hydraulic, pneumatic or electric solenoid or motor-operated equipment: Liquidtight flexible non-metallic conduit unless approved by OWNER.
 - a. Exception: NEMA 7 or 9 areas require explosion-proof flexible conduit.
 - 2. Exposed Conduit: Rigid metal conduit or intermediate metal conduit.
 - a. Exceptions:
 - 1) Areas indicated as NEMA 4X or areas with high chlorine presence, use rigid Schedule 40 PVC conduit.
 - 2) Areas indicated as NEMA 7 or NEMA 9 (such as grit and raw sewage rooms), use 316 stainless steel conduit.
 - 3. Concealed Conduit: PVC Schedule 40 conduit unless indicated otherwise. Only allowed above drop ceilings and behind drywall.
- C. Minimum size conduit shall be 1 inch unless shown otherwise or approved by WRC.
- D. Instrument Signal Conduit Requirements: Shielded signal wires for 4-20 mA type instruments or thermocouple wires assigned to the same control panel may be run in the same conduit. Shielded instrument signal wires, thermocouple wires, and shielded 2-wire intercom wires may be run in the same conduit. No other wires will be permitted in an instrument signal/2-wire intercom conduit. Conduit shall be rigid.
- E. Conduit Thread Paint: Make threaded conduit joints watertight by coating threaded portions with a spray-on or brush-on zinc-bearing paint. Provide paint containing 90 percent minimum by weight of metallic zinc powder in the dried film. Clean field-cut threads of oil using the recommended solvent prior to coating threads.
- F. Install expansion fittings in all exposed rigid nonmetallic conduit runs of 20 feet or more.

- G. Install expansion/deflection fittings where conduit passes a building expansion joint or where conduits are attached to two structures joined by a concrete expansion joint.
- H. Exposed or Concealed Construction: Install conduit exposed inside buildings except for areas with finished walls (e.g., offices, laboratories, lavatories, locker rooms, etc.) unless otherwise indicated. No conduits shall be embedded in concrete or cinderblock walls or floors. Concealed conduits allowed above drop ceilings or behind drywall only.
- I. Exposed Raceways: Install parallel and perpendicular to nearby surfaces or structural members and follow the surface contours as much as practical. Make bends and offsets so the inside diameter is not effectively reduced. Keep the legs of a bend in the same plane and the straight legs of offsets parallel. Conduits shall slope away from loads to keep moisture from entering the load. Run parallel or banked raceways together. Make bends in parallel or banked runs from the same centerline so that the bends are parallel. Factory elbows may be used in banked runs only where they can be installed parallel. This requires that there be a change in the plane of the run, such as from wall to ceiling and that the raceways be of the same size. In other cases, provide field bends for parallel raceways. Keep raceways at least 6 inches away from parallel runs of flues and steam or hot water pipes. Install horizontal raceway runs above water and steam piping.
- J. Space raceways, fittings, and boxes 0.25 inch from mounting surface in NEMA 4 and NEMA 7 areas. Spacers shall be one-piece construction of stainless steel, PVC, ABS, or other noncorrosive material.
- K. Sleeves: Install in concrete floor slabs except where conduit passes through a housekeeping pad. Install in exterior walls below grade.
- L. Stub-up Connections: Extend conduits through concrete floor for connection to freestanding equipment with an adjustable top or coupling threaded inside for plugs and set flush with the finished floor. Extend conductors to equipment with rigid metal conduit; flexible metallic conduit may be used 6 inches above the floor. Where equipment connections are not made under this Contract, install screwdriver-operated threaded plugs flush with floor.
- M. Flexible Connections: Use short length (maximum 6 feet for lighting fixtures; maximum 3 feet for all other equipment) of flexible conduit for recessed and semi-recessed lighting fixtures, equipment subject to vibration, noise transmission, or movement, and all motors. Use liquidtight flexible conduit in wet locations and rated stainless steel flexible connections for hazardous locations. Install separate ground conductor across flexible connections.
- N. Join raceways with fittings designed and approved for the purpose and make joints tight. Where joints cannot be made tight, use bonding jumpers to provide electrical continuity of the raceway system. Where terminations are subject to vibration, use bonding bushings or wedges to assure electrical continuity. Where subject to vibration or dampness, use insulating bushings to protect conductors.
- O. Use raceway fittings that are of types compatible with the associated raceway and suitable for the use and location. For intermediate metal conduit, use threaded rigid metal conduit fittings. For PVC externally coated rigid metal conduit, use only factory-coated fittings approved for use with that material. Patch all nicks and scrapes in PVC coating after installing conduit.

- P. Install raceway sealing fittings in accordance with the manufacturer's written instructions. Locate fittings at suitable, approved, accessible locations and fill them with UL listed sealing compound. Install raceway sealing fittings at the following points and elsewhere as indicated:
1. Where conduits enter or leave hazardous locations.
 2. Where conduits enter or leave NEMA 4X areas.
 3. Where conduits pass from warm locations to cold locations, such as the boundaries of refrigerated spaces and air-conditioned spaces.
 4. Where required by the NEC.
- Q. Threaded covers and fasteners on an explosion proof box and plate, need to be coated with a conductive oxidation inhibitor. Approved include: Ideal NOALOX conductive, Gardener Bender Ox-GardInstall.
- R. Electrical boxes in those locations which ensure ready accessibility to enclosed electrical wiring. Provide knockout closures to cap unused knockout holes where blanks have been removed. In wet or damp areas, oil seals are required.
- S. Install device boxes at the height above the floor as follows for:
1. Light switches, 4 feet.
 2. Receptacles and telephone jacks, 18 inches except in NEMA 4 and 4X areas, 4 feet.
 3. Thermostats, 4'-0".
 4. Clock receptacles, 7'-0".
- T. Avoid installing boxes back-to-back in walls. Provide not less than 6-inch (150 mm) separation.
- U. Position recessed outlet boxes accurately to allow for surface finish thickness.
- V. Fasten electrical boxes firmly and rigidly to structural surfaces to which attached.
- W. Provide fire-retardant barriers in all pull and junction boxes containing circuits that are otherwise continuously separated in conduit. Securely fasten these barriers within box. Size barriers so that space between barrier and box wall does not exceed 0.125 inch anywhere around the perimeter of barrier.
- X. Support exposed raceway within 1 foot of an unsupported box and access fittings. In horizontal runs, support at box and access fittings may be omitted where box or access fittings are independently supported and raceway terminals are not made with chase nipples or threadless box connectors.
- Y. In open overhead spaces, cast boxes threaded to raceways need not be supported separately except where used for fixture support; support sheet metal boxes directly from building structure.
- Z. Terminations: Where raceways are terminated with locknuts and bushings, align the raceway to enter squarely and install the locknuts with dished part against the box. Where terminating in threaded hubs, screw the raceway or fitting tight into the hub so the end bears against the wire protection shoulder. Where chase nipples are used, align the raceway so the coupling is square to the box and tighten the chase nipples so no threads are exposed.
- AA. Complete installation of electrical raceways before starting installation of conductors within raceways and prevent foreign matter from entering raceways by using temporary closure protection.

Cap spare conduit. Protect stub-ups from damage where conduits rise from floor slabs. Arrange so curved portion of bends is not visible above the finished slab.

- BB. Install pull wires in empty raceways: Use No. 14 AWG zinc-coated steel or monofilament plastic line having not less than 200-pound tensile strength. Leave not less than 12 inches of slack at each end of the pull wire.

3.03 WIRE AND CABLE INSTALLATION

- A. Use pulling means including fish tape, cable, rope, and basket weave wire/cable grips which will not damage cables or raceways. Pull conductors simultaneously where more than one is being installed in same raceway. Use UL listed pulling compound or lubricant where necessary.
- B. No cable splices allowed unless approved by OWNER. Splice feeders only where indicated. Use a standard kit. No splices are allowed for instrument and telephone cables except at indicated splice points.
- C. Install crimp terminal connectors which possess equivalent or better mechanical strength and insulation rating than conductors being terminated. Use crimp terminal connectors which are compatible with conductor material and are UL listed as pressure type connectors. No butt-splices are allowed.
- D. Provide adequate length of conductors within electrical enclosures and train conductors to terminal points with no excess beyond service loop. Bundle multiple conductors, with conductors larger than No. 10 AWG cabled in individual circuits. Make terminations so there is no bare conductor at terminal.
- E. Terminate power and control conductors at equipment using pressure-type terminals specifically designed for type of terminations to be made. No Push-in connections are allowed. Terminate no more than 2 conductors No. 8 AWG and smaller within the same pressure-type terminal. These 2 conductors shall be no more than 4 wire gauge sizes apart. Terminate no more than 1 conductor larger than No. 8 AWG within any pressure-type terminal.
 - 1. Exception: Power factor correction capacitor conductors may be terminated at the motor disconnect switch load terminals.
- F. Seal wire and cable ends until ready to splice or terminate.
- G. Provide 10% spare wires in control conduits. Provide minimum of two (2) spares.

3.04 CUTTING AND PATCHING

- A. Perform cutting and patching in accordance with the following requirements:
 - 1. Perform cutting, fitting, and patching of electrical equipment and materials required to uncover Work to provide for installation of ill-timed Work, remove and replace Work that is either defective or does not conform to requirements of Drawings.
 - 2. Cut, remove, and legally dispose of selected electrical equipment, components, and materials as indicated including, but not limited to, removal of electrical items indicated to be removed and items made obsolete by new Work. Protect structure, furnishings, finishes, and adjacent materials not indicated or scheduled to be removed. Provide and maintain temporary partitions or dust barriers adequate to prevent spread of dust and dirt to adjacent areas.

3. Patch existing finished surfaces and building components using new materials matching existing materials.

3.05 EQUIPMENT CHECKOUT AND TESTING

- A. In addition to testing recommended by equipment or material supplier and called for in equipment or material specification, perform the following.
- B. Check-out Procedures. In general, check-out procedures (within the attached spreadsheet) which are applicable for a particular item of equipment shall be performed. In addition, CONTRACTOR is responsible for filling out the Oakland County WRC System Control Unit Activity Log Sheet (Form DC-186).
- C. Motor Testing: Motor insulation shall be tested by using a 500 VDC (minimum) megger and applying test until a constant megohm resistance reading of the following magnitude is obtained:

$$\begin{aligned} R_{\min.} &= 4 (KV + 1) \text{ at } 25 \text{ degrees C winding temp.} \\ R_{\min.} &= KV + 1 \text{ at } 40 \text{ degrees C winding temp.} \end{aligned}$$

1. Definitions:
 - a. R = Insulation Resistance in megaohms
 - b. KV = Motor operating Voltage (in kilovolts)
 2. If motors do not meet requirements of megger test, blow hot air through motors to dry out and repeat until test is passed. If desirable, drying can be done by applying an electrical potential to equipment. However, in no case, induced or direct, shall voltage or current exceed continuous rating of equipment being dried.
 3. After passing megger test, motors shall be hi-pot tested at 200 percent rated voltage for a minimum of 1 minute.
- D. Equipment Testing: The following tests which are applicable for a particular item of equipment shall be performed:
1. Megger bus work phase-to-phase and phase-to-ground. Minimum acceptable steady-state value is 100 megohms.
 2. Megger power circuit breakers and circuits supplied phase-to-phase and phase-to-ground (100 megohms minimum).
 3. Test current transformer circuits by applying current to secondary wiring at current transformer terminals until contactor trips.
 4. Test, time, and set protective relays. Relays shall be timed at various multiples (minimum of 3 points) of the pick-up value to determine agreement with published curves and adjust as necessary to agree with coordination study required settings. Exact tests to be performed vary with type of relay. Manufacturer's instructions for relay shall be complied with.
 5. After Work has been completed, demonstrate to OWNER's Representative that entire electrical installation is in proper working order and will perform functions for which it was designed by functional testing.
 6. Make any specific tests required by the manufacturer's installation instructions.

END OF SECTION